

2 SB 514	Si-P	NF/S-L, 50V, 2A, 20W, 8MHz	17j	BD 244 C	17j	
2 SB 515	Si-P	=2SB514	17j	BD 244 C	17j	
2 SB 516	Ge-P	NF, 20V, 0,1A, 0,15W	2a	AC 151	2a	
2 SB 518(-1,-2)	Si-P	S-L, -1=70V, -2=90V, 7A, 60W, >3MHz	23a	BD 318	23a	
2 SB 519(-1,-2)	Si-P	S-L, -1=90V, -2=110V, 10A, 80W, >3MHz	23a	BD 318	23a	
2 SB 520(-1,-2)	Si-P	S-L, -1=110V, -2=140V, 12A, 100W, >3MHz	23a	2SA1294	18j	
2 SB 521(-1,-2)	Si-P	NF/S-L, -1=60V, -2=85V, 5A, 43W, 7MHz	17j	BD 244 C	17j	
2 SB 522(-1,-2)	Si-P	=2SB521	17j	BD 244 C	17j	
2 SB 523	Si-P	NF/S-L, 40V, 2A, 10W, 70MHz	17j	2SA748	17j	
2 SB 524	Si-P	=2SB523, 60V, 1,5A	17j	2SA748	17j	
2 SB 525	Si-P	Uni, 30V, 1A, 0,8W, 100MHz	7b	2SB892	7c(9mm)	
2 SB 526	Si-P	NF/S-L, 90V, 0,8A, 10W, 70MHz	17j	(2SA748)	17j	
2 SB 527	Si-P	=2SB526: 110V	17j	-	-	
2 SB 528	Si-P	=2SA526: 130V	17j	-	-	
2 SB 529	Si-P	NF/S-L, 40V, 2A, 10W, 70MHz	17j	2SA748	17j	
2 SB 530	Si-P	NF/S-L, 110V, 6A, 80W	23a	BD 318	23a	
2 SB 531	Si-P	NF/S-L, 90V, 6A, 50W, 8MHz	23a	BD 318	23a	
2 SB 532	Si-P	NF/S-L, 80V, 5A, 60W, 10MHz	23a	BD 246 C	18j	
2 SB 533	Ge-P	NF/S, 20V, 2A, 6W(Tc=25°)	2a	-	-	
2 SB 534	Ge-P	NF, 20V, 0,5A, 0,2W	2a	AC 188 K	3a	
2 SB 535	Ge-P	NF/S, 35V, 1A, 0,25W, 6W(Tc=25°)	2a	(AC 188 K)	3a	7
2 SB 536	Si-P	NF/S-L, 130V, 1,5A, 20W, 40MHz	17j	2SB861	17j	
2 SB 537	Si-P	=2SB536	17j	2SB861	17j	
2 SB 538	Ge-P	NF/S-L, 65V, 15A, 75W	23a	-	-	
2 SB 539(A)	Si-P	NF/S-L, 130V, 10A, 100W, 8MHz	23a	2SA1294	18j	
2 SB 539 B	Si-P	=2SB539(A): 150V	23a	2SA1294	18j	
2 SB 539 C	Si-P	=2SB539(A): 160V	23a	2SB817	18j	
2 SB 540	Ge-P	NF/S, 50V, 2A, 6W(Tc=25°)	2a	-	-	
2 SB 541	Si-P	NF/S-L, 110V, 8A, 80W, 9MHz	23a	2SA1294	18j	
2 SB 542	Si-P	Uni, 20V, 0,5A, 0,3W, 150MHz	7b	BC 640	7c	
2 SB 544(MP,P1,P2)	Si-P	Uni, lo-sat, 25V, 1A, 0,9W, 180MHz	7c(9mm)	2SB892	7c(9mm)	
2 SB 546(A)	Si-P	TV-VA, 200V, 2A, 20W, 5MHz	17j	2SB861	17j	
2 SB 547(A)	Si-P	=2SB546(A)	17j	2SB861	17j	
2 SB 548	Si-P	NF-L, 100/80V, 0,8A, 10W, 70MHz	14h	BD 140	14h	
2 SB 549	Si-P	=2SB548: 120/100V	14h	(BD 140)	14h	7
2 SB 550	Si-P	NF/S-L, 100V, 5A, 25W, 20MHz	22a	BD 244 C	17j	
2 SB 551	Si-P	NF/S-L, 50V, 3A, 25W, 32MHz	22a	BD 244 C	17j	
2 SB 552	Si-P	S-L, 220V, 15A, 150W, 3,5MHz	23a	2SA1294	18j	
2 SB 553	Si-P	lo-sat, 70V, 7A, 40W, 10MHz	17j	2SB826	17j	
2 SB 554	Si-P	HIFI-NF-E, 180V, 15A, 150W, 6MHz	23a	MJ 15016	23a	
2 SB 555	Si-P	=2SB554: 140V, 12A, 100W	23a	2SA1294	18j	
2 SB 556	Si-P	=2SB554: 120V, 12A, 100W	23a	2SA1294	18j	
2 SB 557(S)	Si-P	=2SB554: 120V, 8A, 80...100W	23a	2SA1294	18j	
2 SB 558	Si-P	=2SB554: 100V, 7A, 60W	23a	2SA1294	18j	
2 SB 559	Si-P	NF/S-L, lo-sat, 20V, 1,2A, 8W, 150MHz	14h	BD 140	14h	
2 SB 560(MP)	Si-P	Uni, lo-sat, 100V, 0,7A, 0,9W, 100MHz	7c(9mm)	2SB1212	7c(9mm)	
2 SB 561	Si-P	Uni, 25V, 0,7A, 0,5W, 350MHz	7c	(BC 640)	7c	8
2 SB 562	Si-P	=2SB561: 1A, 0,9W	7c(9mm)	(2SB892)	7c(9mm)	8
2 SB 563	Si-P	NF/S-L, 80V, 3A, 25W	22a	BD 244 C	17j	
2 SB 564	Si-P	Uni, 30V, 1A, 1W, 110MHz	9b	BC 640	7c	
2 SB 565(A)	Si-P	NF/S-L, 70V, 4A, 40W, 15MHz	17j	BD 244 C	17j	
2 SB 566(A)	Si-P	=2SB565	17j	BD 244 C	17j	
2 SB 567	Si-P	NF/S-L, 200V, 2A, 30W	17j	2SB861	17j	
2 SB 568	Si-P	=2SB567	17j	2SB861	17j	
2 SB 569	Si-P-Darl	NF/S-L, 40V, 4A, 40W, B=6000	14h	BD 680	14h	
2 SB 570	Si-P-Darl	=2SB569: 60V	14h	BD 680	14h	