

2 SD 2454	Si-N+Di	CTV-HA, 1700/600V, 7A, 50W	18c	-		
2 SD 2455	Si-P	Uni, 40/25V, 1A	40	BC 639	7c	
2 SD 2456	Si-N	Uni, -/40V, 1,5A	40	2SD1207	7c(9mm)	
2 SD 2461	Si-N	hi-beta, 60V, 2A, 1,3W, B>800	12b	(2SC3808)	=14h	4
2 SD 2462	Si-N	hi-beta, 60/60V, 3A, 1,3W, B>800	12b	-		
2 SD 2463	Si-N-Darl+Di	int. Z-Di(B >C), 31V, ±2A, 1W, B>2000	9b	-		
2 SD 2464	Si-N	lo-sat, 15V, 5A, 0,75W, 170MHz, B>300	7c	2SD2179	7c(9mm)	
2 SD 2465	Si-N	L, lo-sat, 40V, 4A, 25W, 120MHz	17c	2SC3299	17c	
2 SD 2465 A	Si-N	=2SD2465: 50V	17c	2SC3299	17c	
2 SD 2466	Si-N	L, lo-sat, 40V, 10A, 40W, 120MHz	17c	-		
2 SD 2466 A	Si-N	=2SD2466: 50V	17c	-		
2 SD 2467	Si-N	=2SD1254:	17c	-		
2 SD 2468	Si-N	=2SD1255:	17c	-		
2 SD 2469(A)	Si-N	=2SD1257(A):	17c	-		
2 SD 2470	Si-N	Blitzg./Strobo, 15V, 5A, 0,4W, 170MHz	41c	2SD2179	9c	
2 SD 2478	Si-N-Darl	L, 80/80V, 4A, 30W, 40MHz, B>1000	17c	(2SD1415)	17c	8
2 SD 2479	Si-N-Darl+Di	L, 120V, 2A, 1,5W, 150MHz, B>4000	78b	-		
2 SD 2480	Si-N-Darl+Di	100V, 2A, 1,3W, 100MHz, B>2000	12b	-		
2 SD 2481	Si-N-Darl+Di	30V, 1,5A, 1,3W, B>4000, 180/900ns	12b	(2SD947)	14b	4
2 SD 2484	Si-N	lo-sat, 50V, 2A, 0,9W	7c(9mm)	2SD1207	7c(9mm)	
2 SD 2485	Si-N	=2SD2484: 80V	7c(9mm)	-		
2 SD 2486	Si-N	hi-beta, lo-sat, 60V, 5A, 70MHz, B>500	17c	-		
2 SD 2491	Si-N	Vid-E, 160/160V, 0,1A, 8W, 140MHz	14b	(2SC3601)	14h	3
2 SD 2492	Si-N	=2SD2491: 200/200V	14b	(2SC3601)	14h	3
2 SD 2497	Si-N	lo-sat, 40/20V, 5A, 0,75W	7c	(2SD2179)	9c	17
2 SD 2498	Si-N	CTV-HA, 1500/600V, 6A, 50W	18c	BU 2508 AF	16c	
2 SD 2499	Si-N+Di	CTV-HA, 1500/600V, 6A, 50W	18c	2SD1555	18c	
2 SD 2500	Si-N	TV-HA, 1500/600V, 10A, 50W	18c	2SC4924	18c	
2 SD 2504	Si-N	lo-sat, 15V, 5A, 0,75W, 170MHz, B>300	7c	2SD2179	7c(9mm)	
2 SD 2510	Si-N+Di	HA, 1500V, 3A, -IBp=2A, 60W	18c	2SD1555	18c	
2 SD 2511	Si-N	HA, 1500V, 3A, -IBp=2A, 60W	18c	2SD1577	16c	
2 SD 2512	Si-N+Di	HA, 1500V, 5A, -IBp=2,5A, 80W	18c	2SD1555	18c	
2 SD 2513	Si-N	HA, 1500V, 5A, -IBp=2,5A, 80W	18c	2SD1577	16c	
2 SD 2514	Si-N+Di	HA, 1500V, 7A, -IBp=3A, 100W	18c	BU 2508 DF	16c	
2 SD 2515	Si-N	HA, 1500V, 7A, -IBp=3A, 100W	18c	BU 2508 AF	16c	
2 SD 2521	Si-N+Di	HA, 1700V, 2,5A, -IBp=1,5A, 60W	18c	-		
2 SD 2522	Si-N+Di	HA, 1700V, 4A, -IBp=2,5A, 80W	18c	-		
2 SD 2523	Si-N+Di	HA, 1700V, 6A, -IBp=3A, 90W	18c	-		
2 SD 2524	Si-N+Di	HA, 1700V, 8A, -IBp=4,5A, 100W	18c	-		
2 SD 2525	Si-N	NF, 60V, 3A, 1,8W, 3MHz	15c	-		
2 SD 2526	Si-N-Darl+Di	100V, 5A, 1,8W, B=2k...15k	15c	-		
2 SD 2527	Si-N	hi-beta, -/60V, 4A	17c	(2SD1273)	17c	7
2 SD 2528	Si-N	hi-beta, lo-sat, -/60V, 5A	17c	-		
2 SD 2530	Si-N-Darl	-/100V, 5A, B=1k...10k	78	(2SD1415)	17c	4
2 SD 2531	Si-N	NF-L, 60V, 4A, 25W, 3MHz	17c	2SC3299	17c	
2 SD 2536	Si-N-Darl+Di	int. Z-Di(B2->C), 85V, 2A, 0,9W, B>2k	7c(9mm)	-		
2 SD 2538	Si-N-Darl	S-L, -/60V, 2A	17c	2SD1415	17c	
2 SD 2539	Si-N+Di	CTV-HA, 1500/600V, 7A, 50W	18c	2SC4769	18c	
2 SD 2544	Si-N	=2SD2486: 15W	78c	-		
2 SD 2549	Si-N	NF/S-L, -/60V, 3A	17c	2SD1411	17c	
2 SD 2550	Si-N	HA, 1700/600V, 4A, 50W	18c	BUH 517	18c	
2 SD 2551	Si-N	HA, 1700/600V, 5A, 50W	18c	BUH 517	18c	
2 SD 2553	Si-N	HA, 1700/600V, 8A, 50W	18c	BUH 517	18c	
2 SD 2554	Si-N-Darl	L, -/160V, 7A, 120W	77j	-		
2 SD 2556	Si-N	lo-sat, -/80V, 5A	30j	2SC3303	30j	
2 SD 2557	Si-N-Darl	S-L, S-Reg, 200/200V, 5A, 70W, B>1500	18j	-		